



RFInnovations

Leaders in Wireless Data

An **STI Engineering** product

I/O Enabled VHF/UHF Data Radio Modem

Crescendo is a series of digital data radio modems designed for use in large scale wide area point-to-point and point-to-multipoint industrial systems.

The radio provides a reliable link over narrow band channels for telemetry and SCADA radio applications requiring information or control of one or multiple remote stations.

The I/O version allows for:

- Remote I/O mirroring mode
- Read & Set all remote pins through AT commands
- Use of I/Os to switch between channels



Features

- I/O support (4 x Analogue 4-20mA, Digital 0-5V or Relay dry contact)
- Frequency Range VHF (148 MHz – 174 MHz) & UHF (380MHz – 520MHz)
- 5 Watt transmit power (software selectable)
- 19,200 bps (or 9,600 bps) air data rate
- Multi-mode LED front panel display for diagnostics, including RSSI meter
- Forward Error Correction (FEC) for high link integrity in RF-noisy environments
- Windows-based GUI support for configuration and remote diagnostics
- Protocol addressing and routing support, DNP-3, Modbus and IEC 870 compatibility
- Store-and-forward repeaters for large-scale networks and coverage expansion
- Pseudo full-duplex operation with automatic repeat request (ARQ)
- Two RS-232 serial ports (main and auxiliary)
- Auto-negotiating 10BASE-T and 100BASE-TX Half and Full-duplex Ethernet
- Operating voltage 9 to 30 VDC

STI Engineering

STI Engineering Pty Ltd

ABN 97 065 523 579

22 Boulder Road Malaga 6090
Western Australia

Telephone: +61 8 9209 0900

Facsimile: +61 8 9248 2833

Email: sales@stiengineering.com.au

Web: www.stiengineering.com.au

Applications

The Crescendo series is suited for applications in Utilities, Mining and Transport industries where reliable long distance data transfer is critical.

The data radio can be used in small- or large-scale telemetry systems, with almost any PLC, RTU, HMI or DCS vendor for monitoring and control of critical assets.

The I/O Model provides access to analog and digital inputs and outputs in a simple, ready to use package with no need to program.

Applications include railway monitoring, pump station and tank control, irrigation, fan and pressure control, and environmental monitoring.

The radios are also used in complex GPS systems for fleet tracking and management, and high precision correctional systems for machine control and automation.

Specifications

Switching Bandwidth	The user can select any 6.25kHz raster frequencies with the easy-to use Windows configuration software.
Data Reliability	User selectable Automatic Repeat Request (ARQ) offers a high level of data reliability. The immediate re-transmission of data ensures that the user will not encounter end to end errors or data loss even in hostile environments.
Diagnostics at a Glance	The front panel LEDs display diagnostic information indication such as Receive Signal Strength (RSSI), transmit power, radio temperature and RS232 port status.
Data Mode Options	With data and frame-driven modes available, the Ethernet Crescendo supports point-to-point, point-to-multipoint, Hayes Dial-up and multiple modes of communication.
Easy Network Management	The user is able to view diagnostics and change the settings of other remote radios within a network from a single point.
Data Integrity	Over the air data is encapsulated with Forward Error Correction, data interleaving and Cyclic Redundancy Checksums (CRC) for high level data protection. This reduces the number of errors in each transmission.
Easy Network Configuration	The Cruise Control software allows the user to configure, save and upload radio configuration settings. This allows for numerous radios to be configured more efficiently.

<p>PHYSICAL Dimensions: 188mm x 100mm x 42mm Weight: 800g Construction: Powder coated aluminium</p> <p>MODEM Serial Data: RS-232 Asynchronous with handshaking Ethernet Data: Transparent IP links using TCP/IP gateway feature Interface Speed: 110bps to 115200bps software selectable Error Rate: -108 dBm for less than 1x10⁻⁶ BER (9600bps) -106 dBm for less than 1x10⁻⁶ BER (19200bps)</p> <p>GENERAL Operating Voltage: 9V to 30V DC (negative ground) Operating Current: - Transmit @12V 1.7A nominal @ 5W - Receive @12V 1A nominal Operating Temp: -20 to +70°C Operating Humidity: Up to 95% non-condensing relative humidity</p>	<p>CONNECTORS Antenna: BNC Female (50 Ohm), Dual BNC for Split Tx/Rx port option Ethernet port: RJ45 (Straight through) Serial: 2 x DB9 RS-232 Female Power: Phoenix PH-1776508 (2 positions) Mating connector supplied</p> <p>RADIO Frequency Range: 148 MHz to 174 MHz Air Data Rate: 19.2 kbps (25 kHz channel), 9.6 kbps (12.5 kHz channel) Duty Cycle: Up to 100% Channel Bandwidth: 12.5kHz or 25kHz (model specific) Compliance: Designed to ACA and FCC Modulation: Nyquist-shaped 4-level FSK Tx key up Time: less than 1mS Data Turn-around Time: <10mS Transmit Power: 1.0mW (0dBm) to 5W (+37dBm) Mode of Operation: Single-port half duplex, Split-port half duplex</p>	<p>OPTIONS RFI-450 HNMEID: Ethernet Enabled Crescendo UHF, Half Duplex, Narrow Band, 9600bps, I/O Module RFI-450 HWHEID: Ethernet Enabled Crescendo UHF, Half Duplex, Wide Band, 19200bps, I/O Module RFI-150 HWHEID: Ethernet Enabled Crescendo VHF, Half Duplex, Wide Band, 19200bps, I/O Module RFI-150 HNMEID: Ethernet Enabled Crescendo VHF, Half Duplex, Narrow Band, 9600bps, I/O Module RFI-150 HNMIID – YYZ where: YY= 12: 12V nominal input voltage 24: 24V nominal input voltage Z= A: 4 Digital In, 4 Relay Out B: 2 Analog 0-5V In, 2 Digital In, 2 Analog 0-5V Out, 2 Relay Out C: 4 Analog 0-5V In, 4 Analog 0-5V Out D: 4 Analog 4-20mA In, 4 Analog 4-20mA Out</p>
--	---	--

V171108



Power connector, Ethernet connector & RF Connector



RS232 connectors & I/O connectors